

TRACK CONNECTORS

120V Track System

WAC LIGHTING

Responsible Lighting®



Fixture Type:

Catalog Number:

Project:

Location:

Track Connectors	Model	Finish	Description	
Live End Connector	HLE H Track	BK Black BN* Brushed Nickel WT White DB** Dark Bronze	Use for direct wiring through ceiling. A canopy plate is required when using with a standard junction box.	
	LLE L Track			
	JLE J Track			
	J2-LE J2 Track			
Live End BX Connector	HBXLE H Track		Use with surface mounted BX or non-metallic sheathed cable. Also provides through the ceiling connection.	
	LBXLE L Track			
	JBXLE J Track			
	J2-BXLE J2 Track			
"I" Power Connector	HI-PWR H Track			Power entry point at the connection of 2 tracks.
	LI-PWR L Track			
	JI-PWR J Track			
	J2-IPWR J2 Track			
"L" Connector Left	HL-LEFT H Track	Use to join 2 track sections to make power feedable 90° left polarity turns.		
	LL-LEFT L Track			
	JL-LEFT J Track			
	J2-LLEFT J2 Track			
"L" Connector Right	HL-RIGHT H Track		Use to join 2 track sections to make power feedable 90° right polarity turns.	
	LL-RIGHT L Track			
	JL-RIGHT J Track			
	J2-LRIGHT J2 Track			
"T" Connector	HT H Track			Use to join 3 track sections. Power feedable on H and J only. "T" Connector with opposite polarity can be custom ordered.
	LT L Track			
	JT J Track			
	J2-T J2 Track			
"X" Connector	HX H Track	Use to join 4 track sections. Power feedable on H and J only.		
	LX L Track			
	JX J Track			
	J2-X J2 Track			
"I" Connector	HI H Track		Use to join two sections of track with electrical continuity.	
	LI L Track			
	JI J Track			
	J2-I J2 Track			
"I" Dead End Connector	HI-DEC H Track			Joins two sections of track without electrical continuity.
	LI-DEC L Track			
	JI-DEC J Track			
	J2-IDEC J2 Track			
Flexible Track Connector	HFLX H Track	Connects two track sections at variable angles. Use as a transition from wall-to-wall, wall-to-ceiling, or ceiling-to-ceiling. Power feedable.		
	LFLX L Track			
	JFLX J Track			
	J2-FLX J2 Track			
Floating Canopy Connector	HFC H Track		Connects to octagon box. Allows track to be powered anywhere along the length of the track.	
	LFC L Track			
	JFC J Track			

*BN finish only available for H, L, J Track **DB finish only available for H Track

WAC Lighting
www.waclighting.com
Phone (800) 526.2588 • Fax (800) 526.2585

Headquarters/Eastern Distribution Center
44 Harbor Park Drive • Port Washington, NY 11050
Phone (516) 515.5000 • Fax (516) 515.5050

Western Distribution Center
1750 Archibald Avenue • Ontario, CA 91760
Phone (800) 526.2588 • Fax (800) 526.2585